

USER MANUAL
BAZOOKA 12
12-INCH SINGLE VOICE COIL



CAOS
UNLIMITED
www.caosunlimited.com

1
Year Warranty



PRODUCT INFORMATIONS

GENERAL SPECIFICATIONS

Nominal Diameter: 12 inches
Rated Impedance: 1*4 ohms
Operating Bandwidth: 40HZ-- 3000HZ
Power Handling Capacity: 800 W(Max)
Sensitivity :93 dB
Voice Coil Diameter: 1.5 inches

PHYSICAL INFORMATIONS

Basket: Steel
Magnet Type: 30 OZ
Cone Material: Non pressed paper
Surround: Foam
Dust Cap: PP
Damper: Cloth
Packing Quantity: 1

THIELE-SMALL PARAMETERS

Bass Reflex Subwoofer system included

It is difficult to give exact box dimensions that are universal for all cars and trucks. It is for this reason that you must be able to calculate the space in which you have available in order to achieve the proper air volume required.

It is recommended to build your enclosure from 3/4" thick MDF (medium density fiberboard). Make sure the enclosure is sealed air tight.

CALCULATING EXTERNAL VOLUME

1)To calculate box volume, measure the outside Width x Height x Depth of the enclosure.
Example $13" \times 15" \times 10" = 1950"$

2)next you must convert cubic inches into cubic feet. To do this, you must divide the cubic inch total by 1728".
Example $1950 : 1728 = 1.128$ Cubic feet

CALCULATING INTERNAL VOLUME

1)To calculate the internal (net) volume of the above box you must first multiply the thickness of the wood you are using by Two (2).
Example $3/4" \times 2" = 1.5"$

2)Next Subtract 1.5 from each of the outside measurements of the box.

Width $13 - 1.5 = 11.5$
Height $15 - 1.5 = 13.5$
Depth $10 - 1.5 = 8.5$

3)Multiply the new totals (H x W x D)
Example $11.5 \times 13.5 \times 8.5 = 1319.625$

4)Next you must convert cubic inches into cubic feet. To do this, you must divide the cubic inch total by 1728"
Example $1319.625 : 1728 = 0.7637$ Cubic feet

